

QG65N2 CANopen High accuracy series

QG65N2-KDXYh-030H-CAN-C(F)M-UL

Inclination sensor


2 axis horizontal mounting

Programmable device

Interface: CANopen

Parameters programmable
by DIS configurator and
CANopen object dictionary

Measuring range
 $\pm 30^\circ$



CANopen



General specifications 12862, 12865, v20221011

| | |
|---|---|
| Housing | Reinforced plastic injection molded (Faradex DS, black, EMI shielded by stainless steel fiber in PC) |
| Dimensions (indicative) | 60x50x27 mm |
| Mounting | Included: 4x M5x25 mm zinc plated steel pozidrive pan head screws, self-tapping (PZ DIN7500CZ) Mounting on flat surface only. Screw crosswise with maximum Torque 2.5 Nm |
| Ingress Protection (IEC 60529) | IP67, IP69K (with IP69K mating connector) |
| Relative humidity | 0 - 95% (non condensing, housing fully potted) |
| Weight | approx. 110 gram |
| Supply voltage | 10 - 32 V dc |
| Polarity protection | Yes |
| Current consumption | 50mA typ. For CFM models (daisy-chained CANbus): max. current internal T-junction: 2.5A |
| Operating temperature | -40 .. +80 °C |
| Storage temperature | -40 .. +85 °C |
| Measuring range | $\pm 30^\circ$ |
| Centering function | Yes (CANout 0 = 0°), range: $\pm 5^\circ$ |
| Frequency response (-3dB) | 0 - 10 Hz |
| Accuracy (overall @20°C) | 0,07° typ. |
| Offset error | $\pm 0,01^\circ$ typ. ($\pm 0,02^\circ$ 2 σ) after centering |
| Non linearity | $\pm 0,06^\circ$ typ., $\pm 0,1^\circ$ 2 σ , $\pm 0,15^\circ$ max. |
| Sensitivity error | not applicable. Repeatability 0,05° |
| Resolution | 0,01° |
| Temperature coefficient | $\pm 0.003^\circ/\text{K}$ typ., $\pm 0.005^\circ/\text{K}$ (2 σ) |
| Max mechanical shock | 10,000g (max 0,2ms) |
| CAN interface (physical layer) | According to ISO 11898-1 & ISO 11898-2 (CAN 2.0 A/B), Short circuit protected |
| CANopen application layer and communication profile | CANopen, CiA301 V4.2.0 & EN 50325-4 + Device Profile CiA410 DSP 2.0.0 for inclinometers |
| Baud rate | 250 kbit/s (default, range 10/20/50/100/125/250/500/800/1000 kbit/s |
| Node Id | 01h (range: 01h - 7Fh) |
| TPDO | For Node ID=01h: TPDO1: 181h, TPDO2: 281h |
| Event time | TPDO1: 10 - 500 ms (default: 100 ms) |
| Sync mode | On/off (default: off) |
| Heartbeat | On/off (default: on, 2s) |
| Programming options | Baudrate, Node Id, Event time, Sync mode, Heartbeat, Output format, CANbus termination, filtering |
| Output format | Integer: -3000 to +3000 (PDO1:X=byte 2,1;Y=byte 4,3) |
| Filtering | Bessel LPF 10Hz on, TPDO averaging off, Output filter off |
| Modes of operation | Event mode, Sync-mode. Default: auto-startup Event mode |
| Internal CANbus termination | 120 Ohm on/off (default: off) |
| Boot time | < 0.5 s |
| Programming options | by optional DIS Configurator and CANopen object dictionary (CAN parameters, filtering) |

QG series

QG65N2-KDXYh-030H-CAN-C(F)M-UL

CANoutput = $100 \cdot \alpha$

Clipping outside measuring range

Zeroing can be done to eliminate mounting offsets.



Default 0°: horizontal (label upwards), no acceleration applied. To eliminate mounting offsets the sensor can be zero-ed within $\pm 5^\circ$ tilt (by the CAN object dictionary)

Cross tilt sensitivity error: $< (0,12 \cdot \text{cross tilt angle})^2 \% \text{ typ.}$

→ one axis $< 10^\circ$ tilt for max. accuracy

Connection

Wire / pin coding




Connectivity (cable length $\pm 10\%$)

Male only or Male & Female (internal T-junction) M12 connector (5 pins, A-coding) (CiA303 V1.8.0) (Brass Nickel coated, contacts copper alloy)

A CANbus always has to be terminated properly according to customers bus topology and general CAN rules. The sensor has an on-board internal 120 Ohm CANbus termination resistor that can be switched on by the CANopen dictionary (default: off). Alternatively an external M12 termination resistor can be connected when using a Male & Female (internal T-junction) model.

External M12 termination resistors and T-connectors are available as accessories, see DIS website.

| | | | |
|--------|---------------|--|--|
| Pin 1: | Shield | | |
| Pin 2: | Vcc | | |
| Pin 3: | Gnd & CAN_GND | | |
| Pin 4: | CAN_H | | |
| Pin 5: | CAN_L | | |



E4ready, UL, CAN-manual, EDS-file, Ordering codes

Before using this device, please read this datasheet, the Manual and the Declaration of Conformity carefully (download from dis-sensors.com)

This product is E4ready and meets Automotive EMC requirements

Connect this sensor only to an approved CAN controller which must have a grounded shield. Alternatively, connect the sensor housing to a grounded shield. All mentioned EMC standards that are met (see Declaration of Conformity) have been done with the housing connected to a grounded shield.

QG series sensors are intended to measure inclination/acceleration/tilt. Flawless function (acc. spec.) is ensured only when used within specifications. This device is not a safety component acc. to EU Machine Directive (ISO13849). For full redundancy two devices can be used. Modifications or non-approved use will result in loss of warranty and void any claims against the manufacturer.

UL & c-UL listed product (File number E312057, UL508 standards UL60947-5-2 & CSA-C22.2 No. 14)
Product Identity / Category Code Number (CCN): Industrial Control Equipment / NRKH & NRKH7
Enclosure rating: type 1, Ambient temperature: max 80 °C (see also datasheet, lowest value applies)
Electrical ratings: Intended to be used with a Class 2 power source in accordance with UL1310, max. input Voltage 32V dc (see also datasheet, lowest value applies), max. current 200mA
Accessory Cable Assembly: Any UL-listed (CYJV/7) mating connector with mechanical locking, wire thickness of at least 30 AWG (0,05 mm²), recommended ≤23 AWG (≥0,25 mm²)

Optional: for accurate mounting two factory mounted positioning pins can be mounted (Ø4mm) replacing 2x M5x25 mm.

As this device is accelerometer-based the sensor is inherent sensitive for accelerations/vibrations.

A CAN-manual can be downloaded from www-dis-sensors.com (type I)
EDS-file (CiA306 V1.3.0) can be downloaded from www-dis-sensors.com (type I)

Ordering codes:

M12 Male: QG65N2-KDXYh-030H-CAN-CM-UL, 12862

M12 Male & Female: QG65N2-KDXYh-030H-CAN-CFM-UL, 12865